# AsteRx-m2

Compact low-power multi frequency GNSS receiver





The AsteRx-m2 is a compact, highperformance, ultra-low power GNSS receiver ideal for integration in UAS, handheld devices and other demanding industrial applications where power and space are at a premium. It incorporates the latest in anti-jamming technology and offers unbeatable robustness and reliability.

### **Key Features**

- Best-in- class reliable and scalable position accuracy
- > AIM+ anti-jamming and monitoring system
- Industry-leading ultra-low power consumption
- All-in-view multi-constellation, multi-frequency satellite tracking
- Easy-to-integrate

For more information contact



+1-703-256-8900 or 800-628-0885 info@NavtechGPS.com www.NavtechGPS.com

## its own in difficult conditions:

- Lock+ for robust tracking during high vibrations and shocks
- APME+ to disentangle direct signal and those reflected from nearby structures
- IONO+ provides advanced protection against ionospheric disturbance

The AsteRx-m2 also features time synchronisation for high-precision timing applications and L-Band tracking for PPP positioning using TerraStar. Two electronically identical antenna connectors support both passive and active antennas.

#### Interference Robustness

The AsteRx-m2 features AIM+, the most advanced onboard anti-jamming technology on the market. It can suppress the widest variety of interferers, from simple continuous narrowband signals to the most complex wideband and pulsed jammers. The RF spectrum can be viewed in real-time in both time and frequency domains.

#### **Ultra-low power Design**

The AsteRx-m2 provides RTK positioning at the lowest power consumption of any comparable device on the market. This means longer operation on a single battery charge, smaller batteries and greater usability.

#### **Easy to Integrate**

The AsteRx-m2 comes with fully-documented interfaces, commands and data messages. The included RxTools software allows receiver configuration and monitoring as well as data logging and analysis. An SDK is provided to help integrators create professional custom applications. The AsteRx-m2 is compatible with GeoTagZ Software and its SDK library for RPK (ReProcessed Kinematic) offline processing.

#### FEATURES

#### Technology

448 hardware channels for simultaneous tracking of all visible satellite signals

- GPS: L1, L2, L5
- · GLONASS: L1, L2, L3
- Galileo: E1, E5a, E5b, AltBoc1
- BeiDou: B1, B21
- SBAS: EGNOS, WAAS, GAGAN, MSAS, SDCM (L1, L5)
- IRNSS: L51
- QZSS: L1, L2, L5

Integrated dual channel L-band receiver AIM+ interference mitigation unit against narrow and wide band interference with spectrum analyser

IONO+ advanced scintillation mitigation

APME+ a posteriori multipath estimator for code and phase multipath mitigation

RAIM (Receiver Autonomous Integrity Monitoring)

RTK (base and rover)<sup>1</sup>

PPP (TerraStar services)<sup>1,2</sup>

Moving base 1, 3

#### Formats

Septentrio Binary Format (SBF), fully documented with sample parsing tools NMEA 0183, v2.3, v3.01, v4.0 RINEX v2.x, 3.x RTCM v2.x, 3.x (MSM messages included) CMR v2.0 and CMR+ (CMR+ input only)

#### Connectivity

4 Hi-speed serial ports (LVTTL) 1 USB device port xPPS output (max 100Hz) 2 Event markers SDIO interface for logging (covers µSD, SD, eMMC) Outputs to drive external LEDs General Purpose Output

Time and Frequency synchronisation inputs

For more information contact



+1-703-256-8900 or 800-628-0885 info@NavtechGPS.com www.NavtechGPS.com

#### PERFORMANCE

#### Position accuracy<sup>3,4,5</sup>

|                            | Horizontal | Vertical |
|----------------------------|------------|----------|
| Standalone                 | 1.2 m      | 1.9 m    |
| SBAS                       | 0.6 m      | 0.8 m    |
| DGNSS                      | 0.3 m      | 0.7 m    |
| TerraStar-C <sup>2,6</sup> | 4 cm       | 6 cm     |

#### RTK performance<sup>4,5,7</sup>

| Horizontal accuracy | 0.6 cm + 0.5 ppm |
|---------------------|------------------|
| Vertical accuracy   | 1 cm + 1 ppm     |
| Initialisation      | 7 s              |

#### Velocity accuracy<sup>4,5</sup> 3 cm/s

#### Maximum update rates

| Latency <sup>8</sup> | < 10 ms |
|----------------------|---------|
| Measurements only    | 100 Hz  |
| Position             | 100 Hz  |
|                      |         |

#### **Time precision**

| xPPS Out <sup>9</sup> | 5 ns    |
|-----------------------|---------|
| Event accuracy        | < 20 ns |

#### Time to first fix

| Cold start <sup>10</sup> | < 45 s   |
|--------------------------|----------|
| Warm start <sup>11</sup> | < 20 s   |
| Re-acquisition           | avg. 1 s |

#### Tracking performance (C/N0 threshold)

| Tracking    | 20 dB-Hz |
|-------------|----------|
| Acquisition | 33 dB-Hz |

#### SUPPORTING COMPONENTS

RxTools, a complete and intuitive GUI tool set for receiver control, monitoring, data analysis and conversion.

GNSS Receiver Communication SDK. Available for both Windows and Linux.

#### Optional accessories

- Antennas
- GeoTagZ re-processing Software and SDK library for aerial mapping

#### **PHYSICAL & ENVIRONMENTAL**

| Size                                  | 47.5 x 70 x 7.6 mm           |
|---------------------------------------|------------------------------|
|                                       | 1.87 x 2.75 x 0.29 in        |
| Weight                                | 28 g / 0.987 oz              |
| Input voltage                         | 3.3 VDC ± 5%                 |
| Power consump                         | tion                         |
| GPS/GLO L1/L2                         | 770 mW                       |
| All Signals all GNSS constellations   | 950 mW                       |
| All Signals all constella<br>+ L-Band | tions 1050 mW                |
| Shutdown power mod                    | de 10 mW                     |
| Antenna                               |                              |
| Connectors <sup>12</sup>              | 2 x U.FL                     |
| Antenna supply voltag                 | ge 3-5.5V DC                 |
| Maximum antenna cu                    | rrent 200 mA                 |
| Antenna gain range                    | passive 0 to<br>50 dB active |
| Auto-detection of external antenna    |                              |
| I/O connectors                        |                              |

30 pins Hirose DF40 socket13

60 pins Hirose DF40 socket for expanded connectivity

#### **Environment**

| Operating te        | mperature | -40 °C to +85 °C  |
|---------------------|-----------|-------------------|
|                     |           | -40 °F to +185 °F |
| Storage temperature |           | -55 °C to +85 °C  |
|                     |           | -67 °F to +185 °F |
| Humidity            | 5% to 95% | (non-condensing)  |
| Vibration           |           | MIL-STD-810G      |
| Certification       |           | RoHS              |
|                     |           |                   |

- Optional feature
- Service subscription required 2
- 3 Output rate 20 Hz 4 Open sky conditions
- 5 RMS level
- 6 After convergence
- 7 Baseline < 40 Km
- 8 99.9%
- 9 Including software compensation of sawtooth effect 10 No information available (no almanac, no approximate position)
- Ephemeris and approximate position known
- 12 Second connector for alternative external antenna 13 Backwards compatible with AsteRx-m for easy upgrade

#### **Europe3**

Greenhill Campus Interleuvenlaan 15i 3001 Leuven, Belgium Torrance, CA 90505, USA

+32 16 30 08 00

23848 Hawthorne Blvd

Americas

Suite 200,

+1 310 541 8139

+852 3959 8680

33 Hysan Avenue

Level 901, The Lee Gardens

Causeway Bay, Hong Kong

Asia-Pacific

septentrio

😚 www.septentrio.com 🛛 🚽 sales@septentrio.com 🏻 🈏 @septentrio



Specifications subject to change without notice. Certain features and specifications may not apply to all models. © 2017 Septentrio NV.All rights reserved.