

KEY FEATURES

Easy to integrate rugged package

Two 220 channel Maxwell 6 chips for multi-constellation GNSS support

OmniSTAR VBS / XP / G2 / HP support

Dual antenna inputs for precise heading calculation

Centimeter level position accuracy

Convenience of ethernet connectivity

Supports FDE and RAIM



RUGGED RECEIVER ENCLOSURE HOUSING A DUAL ANTENNA TRIMBLE BD982 OEM GNSS MODULE FOR PRECISE POSITION AND HEADING APPLICATIONS

TRIMBLE® IS COMMITTED TO SUPPORT EVOLVING NEXT GENERATION SATELLITE CONSTELLATIONS WITH HIGH RTK AND HEADING ACCURACIES IN AN EASY TO USE RUGGED ENCLOSURE FOR HIGH LEVELS OF PERFORMANCE AND PRODUCTIVITY.

BX982 GNSS RUGGED RECEIVER ENCLOSURE

The Trimble® BX982 GNSS receiver enclosure is a multi-channel, multi-frequency OEM GNSS receiver which allows OEM's and System Integrators to rapidly integrate centimeter level positioning and precise heading into their application. The Trimble BX982 supports GPS L1/L2/L5 and GLONASS L1/L2 signals. In addition, Trimble is committed to the next generation of modernized GNSS configurations by providing GALILEO compatible products available for customers well in advance of GALILEO system availability. In support of this, the BX982 is capable of tracking the experimental GIOVE A/B test satellites for signal evaluation and test purposes.^{1,2}

DUAL-ANTENNA INPUT

Single antenna GNSS systems have difficulty determining where the antenna is positioned relative to the vehicle and object of interest, especially when dynamics are low. External sensors can be used to augment this however these tend to drift when static. Heading derived from dual-antenna GNSS measurements overcomes these issues and is now economically the right choice. The BX982 harnesses the power of the 220 channel Trimble Maxwell 6 Technology with dual chips supporting two antennas connected to the board. Independent observations from both antennas are passed to the processor where multi-constellation RTK baselines are computed. A single connection to the BX982 via RS232, USB, Ethernet or CAN delivers both centimeter accurate positions and less than a tenth of a degree (2 meter baseline) heading accuracy.

FLEXIBLE INTERFACING

The Trimble BX982 was designed for easy integration and rugged dependability. Customers benefit from the Ethernet connectivity available on the board, allowing high speed data transfer and configuration via standard web browsers. Just like other Trimble embedded technologies; easy to use software commands simplify integration and reduce development times. All software features are password-upgradeable, allowing functionality to be upgraded as your requirements change.

HIGH INTEGRITY

The BX982 supports Fault Detection and Exclusion (FDE) and Receiver Autonomous Integrity Monitoring (RAIM) for safety-critical applications.

RUGGED RECEIVER ENCLOSURE

The Trimble BX982 packages a single BD982 receiver module in a rugged enclosure. The unit comes in an environmentally sealed enclosure that is very easy to install. The BX982 is rigorously tested to perform in harsh environmental conditions with the reliability you expect from Trimble.

TRIMBLE BX982 RUGGED RECEIVER ENCLOSURE

TECHNICAL SPECIFICATIONS¹

- Position Antenna based on 220 Channel Maxwell 6 chip:
 - GPS: Simultaneous L1 C/A, L2E, L2C, L5
 - GLONASS: Simultaneous L1 C/A, L1 P, L2 C/A, L2 P
 - SBAS: Simultaneous L1 C/A, L5
 - GIOVE-A: Simultaneous L1 BOC, E5A, E5B, E5AltBOC
 - GIOVE-B: Simultaneous L1 CBOC, E5A, E5B, E5AltBOC
 - GALILEO: Simultaneous L1 CBOC, E5A, E5B, E5AltBOC²
- Vector Antenna based on second 220 Channel Maxwell 6 chip:
 - GPS: Simultaneous L1 C/A, L2E, L2C
 - GLONASS: Simultaneous L1 C/A, L1 P, L2 C/A, L2 P
- Advanced Trimble Maxwell Custom GNSS Technology
- High precision multiple correlator for GNSS pseudorange measurements
- Unfiltered, unsmoothed pseudorange measurements data for low noise, low multipath error, low time domain correlation and high dynamic response
- Very low noise GNSS carrier phase measurements with <1 mm precision in a 1 Hz bandwidth
- Proven Trimble low elevation tracking technology
- 1 USB port
- 1 CAN port
- 1 LAN Ethernet port:
 - Supports links to 10BaseT/100BaseT networks
 - All functions are performed through a single IP address simultaneously— including web GUI access and raw data streaming
 - Network Protocols supported
 - HTTP (web GUI)
 - NTP Server
 - NMEA, GSOE, CMR over TCP/IP or UDP
 - NTripCaster, NTripServer, NTripClient
 - mDNS/uPnP Service discovery
 - Dynamic DNS
 - eMail alerts
 - Network link to Google Earth
 - Support for external modems via PPP
- 3 x RS232 ports
 - Baud rates up to 460,800
- 1 Hz, 2 Hz, 5 Hz, 10 Hz, 20 & 50 Hz positioning outputs (depends on installed option)
- Up to 50 Hz raw measurement & position outputs
- Reference outputsCMR, CMR+, sCMRx, RTCM 2.1, 2.2, 2.3, 3.0, 3.1
- Navigation outputsASCII: NMEA-0183 GSV, AVR, RMC, HDT, VGK, VHD, ROT, GKG, GGA, GSA, ZDA, VTG, GST, PJT, PJK, BPQ, GLL, GRS, GBS and Binary: Trimble GSOE
- Control Software: HTML web browser. Internet Explorer 7.0 or later, Firefox 3.5 or later, Safari 4.0, Opera 9, Google Chrome
- 1 Pulse Per Second Output
- Event Marker Input Support

POSITIONING SPECIFICATIONS³

| Mode | Accuracy ⁴ | Latency ⁵ | Maximum Rate |
|-------------------|----------------------------|----------------------|--------------|
| Single Baseline | 0.008 m + 1 ppm Horizontal | <20 ms | 50 Hz |
| RTK (<30 km) | 0.015 m + 1 ppm Vertical | | |
| DGPS | 0.25 m + 1 ppm Horizontal | <20 ms | 50 Hz |
| | 0.50 m + 1 ppm Vertical | | |
| SBAS ⁶ | 0.50 m Horizontal | <20 ms | 50 Hz |
| | 0.85 m Vertical | | |

RTK initialization time³ typically <10 seconds
 RTK initialization reliability³ typically >99.9%

HEADING SPECIFICATIONS³

| Baseline | Accuracy ⁴ | Maximum Rate |
|----------|-----------------------|--------------|
| 1 m | <0.15° | 50 Hz |
| 2 m | <0.09° | 50 Hz |
| 10 m | <0.05° | 50 Hz |

PERFORMANCE SPECIFICATIONS

| | |
|--|-------------|
| Time to First Fix (TTFF) ⁷ | |
| Cold Start ⁸ | <45 seconds |
| Warm Start ⁹ | <30 seconds |
| Signal Re-acquisition | < 2 seconds |
| Velocity Accuracy ^{3,4} | |
| Horizontal | 0.007 m/sec |
| Vertical | 0.020 m/sec |
| Acceleration | 11 g |
| Maximum Operating Limits ¹⁰ | |
| Velocity | 515 m/sec |
| Altitude | 18,000 m |

PHYSICAL AND ELECTRICAL CHARACTERISTICS

| | |
|--------------------------|------------------------------------|
| Size | 261 mm x 140 mm x 55 mm |
| Power | 9 V DC to 28 V DC Maximum 4.1 W |
| Weight | 1.6 kg |
| Connectors | |
| I/O | .D-sub DE9 and DA26 |
| Antenna | TNC |
| Antenna LNA Power Output | |
| Voltage | 5 V DC |

ENVIRONMENTAL CHARACTERISTICS¹¹

| | |
|----------------------------|--|
| Temperature | |
| Operating | -40 °C to +70 °C |
| Storage | -55 °C to +85 °C |
| Vibration | MIL810F, tailored Random 6.2 gRMS operating Random 8 gRMS survival |
| Mechanical shock | MIL810D ±40 g operating ±75 g survival |
| IP Rating | IP67 |

ORDERING INFORMATION

Module Trimble BX982 GNSS receiver enclosure available in a variety of configurations from L1 DGPS upwards

1 Trimble BX982 is available in a variety of software configurations. Specifications shown reflect full capability.
 2 Developed under a license of the European Union and the European Space Agency.
 3 May be affected by atmospheric conditions, signal multipath, satellite geometry and placement of antennas. Initialization reliability is continuously monitored to ensure highest quality.
 4 1 sigma level, when using Trimble Zephyr™ 2 antennas.
 5 At maximum output rate.
 6 GPS only and depends on SBAS System performance. FAA WAAS accuracy specifications are <5 m 3DRMS.
 7 Typical observed values.
 8 No previous satellite (ephemerides / almanac) or position (approximate position or time) information.
 9 Ephemerides and last used position known.
 10 As required by the U.S. Department of Commerce to comply with export licensing restrictions.
 11 Dependent on appropriate mounting/enclosure design.

Specifications subject to change without notice.

© 2012, Trimble Navigation Limited. All rights reserved. Trimble and the Globe & Triangle logo are trademarks of Trimble Navigation Limited, registered in the United States and in other countries. PN 022510-105 (02/12)



AMERICAS & ASIA-PACIFIC
TRIMBLE NAVIGATION LIMITED
 Integrated Technologies
 510 DeGuigne Drive
 Sunnyvale, CA 94085
 USA
 +1-408-481-8070 Phone
 +1-408-481-8984 Fax
 Email: sales-intech@trimble.com

EUROPE & MIDDLE EAST
TRIMBLE GERMANY GmbH
 Integrated Technologies
 Am Prime Parc
 1165479 Raunheim,
 Germany
 Phone +49 (6142) 177-2135
 Fax +49 (6142) 177-2136
 emeasales-intech@trimble.com

CHINA
TRIMBLE NAVIGATION LIMITED
 Integrated Technologies
 311 Fute (M) Road, 3/F
 Wai Gaoqiao Free Trade Zone
 Pudong, Shanghai 200131
 China
 Email: chinasales-intech@trimble.com

RUSSIA
TRIMBLE NAVIGATION LIMITED
 Integrated Technologies
 Tel: +7 495 5041081
 Email: rusales-intech@trimble.com
www.trimble.com/gnss-inertial